



●EKEMDL21AR-KIT (Chip Common Mode Choke Coils)

No.	Part Number	Quantity (pcs.)	Common Mode Impedance (at 100MHz, 20 degrees C)	Rated Voltage (Vdc)	Rated Current (mA)
1	DLW21HN670SQ2	10	67Ω±25%	50	330
2	DLW21HN900SQ2	10	90Ω±25%	50	330
3	DLW21HN121SQ2	10	120Ω±25%	50	280
4	DLW21HN181SQ2	10	180Ω±25%	50	250
5	DLW21HN670HQ2	10	67Ω±25%	20	240
6	DLW21HN900HQ2	10	90Ω±25%	20	220
7	DLW21HN121HQ2	10	120Ω±25%	20	200
8	DLW21SN501SK2	10	500Ω±25%	50	250
9	DLW21SN921SK2	10	920Ω±25%	50	160
10	DLW21SN670SQ2	10	67Ω±25%	50	400
11	DLW21SN900SQ2	10	90Ω±25%	50	330
12	DLW21SN121SQ2	10	120Ω±25%	50	370
13	DLW21SN181SQ2	10	180Ω±25%	50	330
14	DLW21SN261SQ2	10	260Ω±25%	50	300
15	DLW21SN371SQ2	10	370Ω±25%	50	280
16	DLW21SN670HQ2	10	67Ω±25%	20	320
17	DLW21SN900HQ2	10	90Ω±25%	20	280
18	DLW21SN121HQ2	10	120Ω±25%	20	280
19	DLW21SR670HQ2	10	67Ω±25%	20	400
20	DLW21SN181XQ2	10	180Ω±25%	20	240
21	DLW21SN261XQ2	10	260Ω±25%	20	220
22	DLW21SN491XQ2	10	490Ω±25%	20	190
23	DLP0NSC280HL2	10	28Ω±20%	5	100
24	DLP0NSN350HL2	10	35Ω±10Ω	5	100
25	DLP0NSN670HL2	10	67Ω±20%	5	110
26	DLP0NSN900HL2	10	90Ω±20%	5	100
27	DLP0NSN121HL2	10	120Ω±20%	5	90
28	DLP0NSA070HL2	10	7Ω±2Ω	5	100
29	DLP0NSA150HL2	10	15Ω±5Ω	5	100
30	DLP0QSN600HL2	10	60Ω±25%	5	50
31	DLP0QSA070HL2	10	7Ω±2Ω	5	100
32	DLP0QSA150HL2	10	15Ω±5Ω	5	100
33	DLP0QSA350HL2	10	35Ω±10Ω	5	100
34	DLP1NDN350HL4	10	35Ω±20%	5	100
35	DLP1NDN670HL4	10	67Ω±20%	5	80
36	DLP1NDN900HL4	10	90Ω±20%	5	60
37	DLP11SA350HL2	10	35Ω±20%	5	170
38	DLP11SA670HL2	10	67Ω±20%	5	150
39	DLP11SA900HL2	10	90Ω±20%	5	150
40	DLP11SN670SL2	10	67Ω±20%	5	180
41	DLP11SN121SL2	10	120Ω±20%	5	140
42	DLP11SN161SL2	10	160Ω±20%	5	120
43	DLP11SN900HL2	10	90Ω±20%	5	150
44	DLP11SN201HL2	10	200Ω±20%	5	110
45	DLP11SN241HL2	10	240Ω±20%	5	100
46	DLP11SN281HL2	10	280Ω±20%	5	90
47	DLP11SN331HL2	10	330Ω±20%	5	80
48	DLP11RB150UL2	10	15Ω±5Ω	5	100
49	DLP11RB400UL2	10	40Ω±10Ω	5	100
50	DLP11RN450UL2	10	45Ω±25%	5	100
51	DLP11TB800UL2	10	80Ω±25%	5	100
52	DLP2ADA350HL4	10	35Ω±20%	5	150
53	DLP2ADA670HL4	10	67Ω±20%	5	130
54	DLP2ADA900HL4	10	90Ω±20%	5	120
55	DLP2ADN670HL4	10	67Ω±20%	5	140

Continued on the following page. 

Continued from the preceding page.

No.	Part Number	Quantity (pcs.)	Common Mode Impedance (at 100MHz, 20 degrees C)	Rated Voltage (Vdc)	Rated Current (mA)
56	DLP2ADN900HL4	10	90Ω±20%	5	130
57	DLP2ADN121HL4	10	120Ω±20%	5	120
58	DLP2ADN161HL4	10	160Ω±20%	5	100
59	DLP2ADN201HL4	10	200Ω±20%	5	90
60	DLP2ADN241HL4	10	240Ω±20%	5	80
61	DLP2ADN281HL4	10	280Ω±20%	5	80
62	DLM11SN450HY2	10	45Ω±25%	5	100
63	DLM11SN900HY2	10	90Ω±25%	5	100

● EKEMDCC5AG-KIT (Chip Common Mode Choke Coils for DC Power Lines / SMD Block Type EMIFIL® for Power Lines)

No.	Part Number	Quantity (pcs.)	Common Mode Impedance (at 100MHz, 20 degrees C)	Rated Voltage (Vdc)	Rated Current (mA)
1	DLW44SN401SK2	5	400Ω (Typ.)	60	2100
2	DLW44SN851SK2	5	850Ω (Typ.)	60	1900
3	DLW44SN172SK2	5	1700Ω (Typ.)	60	1500
4	DLW44SN242SK2	5	2400Ω (Typ.)	60	1400
5	DLW44SN302SK2	5	2200Ω (Typ.)	60	1100
6	DLW5AHN402SQ2	5	4000Ω (Typ.)	50	200
7	DLW5ATN111SQ2	5	110Ω (Typ.)	50	5000
8	DLW5ATN401SQ2	5	400Ω (Typ.)	50	2000
9	DLW5ATN501SQ2	5	500Ω (Typ.)	50	1500
10	DLW5ATN851SQ2	5	850Ω (Typ.)	50	1500
11	DLW5ATN272SQ2	5	2700Ω (Typ.)	50	1000
12	DLW5ATN500MQ2	5	50Ω (Typ.)	50	6000
13	DLW5ATN151MQ2	5	150Ω (Typ.)	50	5000
14	DLW5ATN331MQ2	5	330Ω (Typ.)	50	4000
15	DLW5ATN501MQ2	5	500Ω (Typ.)	50	2500
16	DLW5ATN112MQ2	5	1100Ω (Typ.)	50	2000
17	DLW5BSM501TQ2	5	500Ω (Typ.)	50	1000
18	DLW5BSM601TQ2	5	600Ω (Typ.)	50	1400
19	DLW5BSM801TQ2	5	800Ω (Typ.)	50	2000
20	DLW5BSM191SQ2	5	190Ω (Typ.)	50	5000
21	DLW5BSM351SQ2	5	350Ω (Typ.)	50	2000
22	DLW5BSM102SQ2	5	1000Ω (Typ.)	50	1500
23	DLW5BSM152SQ2	5	1500Ω (Typ.)	50	1000
24	DLW5BSM302SQ2	5	3000Ω (Typ.)	50	500
25	DLW5BTM101SQ2	5	100Ω (Typ.)	50	6000
26	DLW5BTM251SQ2	5	250Ω (Typ.)	50	5000
27	DLW5BTM501SQ2	5	500Ω (Typ.)	50	4000
28	DLW5BTM102SQ2	5	1000Ω (Typ.)	50	2000
29	DLW5BTM142SQ2	5	1400Ω (Typ.)	50	1500

● EKEMDL5AAC-KIT (Chip Common Mode Choke Coils for DC Power Lines / SMD Block Type EMIFIL® for Power Lines / 105 degree C available Type)

No.	Part Number	Quantity (pcs.)	Common Mode Impedance (at 100MHz, 20 degrees C)	Rated Voltage (Vdc)	Rated Current (mA)
1	DLW5ATN500MQ2	5	50Ω (Typ.)	50	6000
2	DLW5ATN151MQ2	5	150Ω (Typ.)	50	5000
3	DLW5ATN331MQ2	5	330Ω (Typ.)	50	4000
4	DLW5ATN501MQ2	5	500Ω (Typ.)	50	2500
5	DLW5ATN112MQ2	5	1100Ω (Typ.)	50	2000
6	DLW5ATN111TQ2	5	110Ω (Typ.)	50	5000
7	DLW5ATN231TQ2	5	230Ω (Typ.)	50	4000
8	DLW5ATN401TQ2	5	400Ω (Typ.)	50	2500
9	DLW5ATN501TQ2	5	500Ω (Typ.)	50	2000
10	DLW5BTM101TQ2	5	100Ω (Typ.)	50	6000
11	DLW5BTM251TQ2	5	250Ω (Typ.)	50	5000
12	DLW5BTM501TQ2	5	500Ω (Typ.)	50	4000
13	DLW5BTM102TQ2	5	1000Ω (Typ.)	50	2500
14	DLW5BTM142TQ2	5	1400Ω (Typ.)	50	2000
15	DLW5BSM501TQ2	5	500Ω (Typ.)	50	1000
16	DLW5BSM601TQ2	5	600Ω (Typ.)	50	1400
17	DLW5BSM801TQ2	5	800Ω (Typ.)	50	2000